

Arcade Legends Computer 3 BIOS Setup

(Black desktop style case)

While the Game is powering up, tap the 'Delete' key once a second until the Setup screen appears.

-----  
Dell Dimension L933x SETUP  
-----

Main - No Changes

Advanced - > Boot Configuration - all set to No  
> Peripheral Configuration - Serial Port A Auto  
- Parallel Port Auto  
- Mode Bi-directional  
- Legacy USB Support Enabled  
- IRQ5 Reserved  
  
> IDE Configuration - IDE Controller Both  
> Diskette Configuration - Diskette Controller Disabled  
- Diskette Drive NOT Installed  
  
> Event Log Configuration - don't care  
> Video Configuration - Primary Video Adapter PCI

Security - do not use

Boot - Quiet Boot Enabled  
Quick Boot Enabled  
  
Restore On AC Power Loss Power On  
On LAN Power On  
On PME Power On  
  
1st Boot Device ATAPI CDROM  
2nd Boot Device IDE-HDD  
3rd Boot Device Disabled

Exit - Exit Saving Changes

**\*Setup Notes:**

- In the event of battery replacement we recommend leaving the battery out for a minimum of 30 minutes before replacing it with a new one.
- This Motherboard is found mostly in Black desktop style cases.
- This computer uses battery number CR-2032.
- Once these changes are made the computer will restart on it's own and should display a logo of some type, then most VGA monitors will 'go to sleep' or display an 'out of range' message if your machine already has the game software installed on the hard drive. This is completely normal and expected if the configuration is correct.