

Nicktoons RACING CPU 2 & CPU 3

Phoenix - AwardBIOS CMOS Setup Utility

- | | |
|--|---|
| <ul style="list-style-type: none"> > Standard CMOS Features > Advanced BIOS Features > Advanced Chipset Features > Intergrated Peripherals > Power Management Setup > PNP / PCI Configurations > PC Health | <ul style="list-style-type: none"> > Frequency / Voltage Control Load Optimized Defaults Set Supervisor Password Set User Password Save & Exit Setup Exit Without Saving Upgrade BIOS |
|--|---|

| | |
|------------------------|-----------|
| Standard CMOS Features | |
| Date | |
| Time | |
| > IDE Primary Master | (HDD) |
| > IDE Primary Slave | |
| > IDE Secondary Master | (CD Rom) |
| > IDE Secondary Slave | |
| Drive A | None |
| Drive B | None |
| Video | EGA / VGA |
| Halt On | No Errors |

Note: HDD & CD Rom may be connected to either IDE port.

| | |
|----------------------------|-------------|
| Advanced BIOS Features | |
| Virus Warning | |
| > Boot Seq & Floppy Setup | Press Enter |
| CPU Internal Cache | Enabled |
| External Cache | Disable |
| CPU L2 Cache ECC Checking | Enabled |
| Quick Power On Self Test | Enable |
| Boot Up NumLock Status | On |
| Gate A20 Options | Fast |
| Typematrice Rate | Disable |
| | |
| | |
| | |
| Security Option | Setup |
| APIC Mode | Enable |
| MPS Version Control for OS | 1.4 |
| OS Select for DRAM | Non-OS2 |
| Video BIOS Shadow | Disabled |
| Summary Screen Show | Disabled |

| | |
|-------------------------|----------|
| Boot Seq & Floppy Setup | |
| First Boot Device | CDROM |
| Second Boot Device | HDD-0 |
| Third Boot Device | Disabled |
| Boot Other Device | Enabled |
| Swap Floppy Drive | Disabled |
| Boot Up Floppy Seek | Disabled |

| Advanced Chipset Features | | OnChip IDE Control | |
|---------------------------|-------------|--------------------------|----------|
| >DRAM Clock/DriveControl | Press Enter | OnChip Primary PCI IDE | Enabled |
| >AGP & P2P Bridge Control | Press Enter | OnChip Secondary PCI IDE | Enabled |
| >CPU & PCI Bus Control | Press Enter | IDE Prefetch Mode | Enabled |
| Memory Hole | Disabled | Primary Master PIO | Auto |
| System BIOS Cacheable | Disabled | Primary Slave PIO | Auto |
| Video RAM Cacheable | Disabled | Secondary Master PIO | Auto |
| VGA Share Memory Size | 16M | Secondary Slave PIO | Auto |
| | | Primary Master UDMA | Disabled |
| | | Primary Slave UDMA | Disabled |
| | | Secondary Master UDMA | Disabled |
| | | Secondary Slave UDMA | Disabled |
| | | IDE HDD Block Mode | Enabled |

| Intergrated Peripherals | | OnChip PCI Device | |
|-------------------------|-------------|----------------------|----------|
| > OnChip IDE Control | Press Enter | VIA-3058 AC97 Audio | Auto |
| > OnChip PCI Devices | Press Enter | VIA-3068 MC97 Modem | Disabled |
| > Super IO Device | Press Enter | VIA-3043 OnChip LAN | Disabled |
| Inot Display First | PCI Slot | Onboard Lan Boot ROM | Disabled |
| OnChip USB Controller | All Enabled | | |
| IDE DMA Transfer Access | Enable | | |

| Power Management Setup | | Super IO Device | |
|----------------------------|-------------|------------------------|------------------|
| ACPI function | Enabled | Onboard FDC Controller | Disabled |
| ACPI Suspend Type | S1(POS) | Onboard Serial Port 1 | 3F8 / IRQ4 |
| Power Management Option | User Define | Onboard Serial Port 2 | Disabled |
| HDD Power Down | Disabled | | |
| Suspend Mode | Disable | | |
| Video Off Option | Suspend Off | Onboard Parrallel Port | 378 / IRQ7 |
| Video Off Method | V/H S Blank | Parrallel Port Mode | ECP + EPP |
| Modem Use IRQ | 3 | EPP Mode Select | EPP 1.7 (or 1.9) |
| Soft-Off By PWRBTN | Instant-Off | ECP Mode Use DMA | 3 |
| State After Power Failure | On | Game Port Address | 201 |
| >Wake Up/Power On Control | Press Enter | Midi Port Address | 330 |
| >Reload Global Timer Event | Press Enter | Midi Port IRQ | 10 |